

Product Code

F09445

DUOX PLUS VEO 4.3" MONITOR

Reference	EAN
9445	8424299094458

Description.

Description

The VEO monitor is made of high-impact ABS plastic. Texturized finish for easy cleaning and ultraviolet protection to get more resistance to the light. VEO incorporates a 4,3" (16:9) panoramic color TFT screen. Its unique handset design incorporating a magnet enables the user to put it back into position correctly when the call is finished. Its balanced design of pure lines is distinguishing, modern and minimal. VEO integrates in the ambience.

When a call is received, the image appears automatically. When the handset is picked up a conversation with the visitor can take place. The image is de-activated automatically after 90 seconds, or when the handset is put back in position. To open the door, press the button with a key.

Technical Details

GENERAL CHARACTERISTICS

- Technology: DUOX PLUS (full digital 2 non-polarized wires)
- Audio/Video System: Color Audio/Video

- Mounting: Surface mounting (request connector ref. 9447 separately)
- Desktop support: Yes (ref. 9410)
- Earpiece with magnet to facilitate hanging: Yes
- Version with inductive loop available: Yes (Exchanging headset for ref. 3443 or request monitor ref. 9455 that already includes the inductive loop)
- Screen dimensions: 4.3" (16:9 Widescreen)
- Screen resolution (H x V): 480 x 272
- Product color: Matte white
- Total buttons: 4
- Type of buttons: Mechanical (silicone)
- Number of LEDs for light signals: 1 (red 3 states: always active, slow/fast flashing)

TERMINAL ADDRESS PROGRAMMING

- From the terminal: From OSD menu
- From the panel or concierge: Yes
- From the panel through the doorbell (without entering the home): Yes

FUNCTIONS

- Automatic photo capture (PHOTOCALLER): Yes (1 photo/call, up to 150 photos, 368 x 288 pixels). This feature can be enabled by the user. Disabled by default.
- Call to concierge center: Yes (from door opening button)
- Auto-on: Yes (up to 3 plates/cameras)
- On-Screen OSD Menu: Yes
- Button for additional function F1: Yes (sending negative and/or command)
- Additional function F2 from screen: Yes (command only, no negative)
- Doorbell with melody differentiated from the plate: Yes
- Connection for device add. (call extension, lights and bells activation, etc.): Yes (ref. 2040, ref. 2438, ref. 3267)
- Additional terminals with the same address: Yes, maximum 2 additional terminals (additional power supply may be required)
- Doormatic (opening function for professionals): No

SETTINGS

- Date and time: Yes
- Melody selection: Yes (5). Configurable for Block Plate 0, Block Plate 1, General Entry Plate 0 and Concierge.
- Call volume regulation: Yes (10 levels per OSD menu)
- Do not disturb function: Yes (via OSD menu) + Red LED signaling
- Conversation audio volume regulation: Yes (10 levels per OSD menu)
- Brightness, contrast and color regulation: Yes (via OSD menu)

TECHNICAL CHARACTERISTICS

- Product dimensions (Width x Height x Depth mm): 200 x 200 x 23 (44 including handset)
- Time to answer or open from when the call occurs: 30 s.
- Talk time: 90s.
- Conversation privacy: Yes
- Supply voltage: 18-24 Vdc
- Maximum consumption (W): 4.56 W
- Standby consumption (W): 0.8 W
- Operating temperature (ºC, ºF); Humidity: [-5ºC, +40ºC][23ºF, 106ºF]; [0%, 90%]
- Line adapter included in the monitor: Yes (A, C, default position OFF)
- Terminals: Bin, Bin, Bout, Bout, -, A+, F1, T

CALL FORWARDING (MOBILE & TABLET APP)

DuoxMe call forwarding (with a subscription model) available at Connected Facilities located in Spain.

Details.

Product measurements (height x width x depth) mm	Product height (mm)	Product width (mm)	Product depth (mm)
200 x 200 x 44	200	200	44

Weight (kg)	Packaging measurements (height x width x depth) cm	Video Door Entry system Technologie
0.53	5,1x22,2x20,7	DUOX

Manuals

- 970143Ac_Guia_rap_Usuario_Monitor_VEO_V05_23.pdf
- 970143Ec_Guia_rap_Usuario_Monitor_VEO_V05_23.pdf
- 970143Fc_Guia_rap_Usuario_Monitor_VEO_V05_23.pdf
- 970143Ic_Guia_rap_Usuario_Monitor_VEO_V05_23.pdf
- 970143Pc_Guia_rap_Usuario_Monitor_VEO_V05_23.pdf
- 970159c_Monitor_VEO_duox_NEW_V05_23.pdf
- 970160b_Guia_rap_monitor_VEO_duox_NEW_V05_23.pdf

Accessories



F09447
DUOX PLUS CONNECTOR



F03389
UNIVERSAL FRAME LARGE



F09410
VEO MONITOR DESKTOP SUPPORT



F03443
VEO TELEPHONE HANDSET W/INDUCT.LOOP

Training video

- https://youtube.com/playlist?list=PLf1YNFmssC37H-1CN64Io6ND28rmVsQit